

The Patent Office
Cardiff Road
Newport
Gwent
NP9 1RH

I, the undersigned, being an officer duly authorised in accordance with Section 62(3) of the Patents and Designs Act 1907, to sign and issue certificates on behalf of the Comptroller-General hereby certify that annexed hereto is a true copy of the documents as originally filed in connection with the Patent application identified therein.

In accordance with the Patents (Companies Re-registration) Rules 1982, if a company named in this certificate and any accompanying documents has re-registered under the Companies Act 1980 with the same name as that with which it was registered immediately before re-registration save for the substitution as, or the inclusion as, the last part of the name of the words "public limited company" or their equivalents in Welsh, references to the name of the company in this certificate and any accompanying documents shall be treated as references to the name with which it is so re-registered.

In accordance with the rules, the words "public limited company" may be replaced by p.l.c., plc, P.L.C. or PLC.

Re-registration under the Companies Act does not constitute a new legal entity but merely subjects the company to certain additional company law rules.


Witness my hand this
13th day of MAY 1991

W. Russell

COC 1

For official use

5 APR 1991



-8APR 791HDD2A3471 PAT 1 77 UC 15.00

Your reference
- P/2224(155)

9107164.7

Notes.

Please type, or write in dark ink using CAPITAL letters. A prescribed fee is payable for a request for grant of a patent. For details, please contact the Patent Office (telephone 071-829 6910).

Rule 16 of the Patents Rules 1990 is the main rule governing the completion and filing of this form.

② Do not give trading styles, for example, 'Trading as XYZ company', nationality or former names, for example, 'formerly (known as) ABC Ltd' as these are not required.

Warning

After an application for a Patent has been filed, the Comptroller of the Patent Office will consider whether publication or communication of the invention should be prohibited or restricted under Section 22 of the Patents Act 1977 and will inform the applicant if such prohibition or restriction is necessary. Applicants resident in the United Kingdom are also reminded that under Section 23, applications may not be filed abroad without written permission unless an application has been filed not less than 6 weeks previously in the United Kingdom for a patent for the same invention and either no direction prohibiting publication or communication has been given, or any such direction revoked.

The
**Patent
Office**

**Request for grant of a
Patent
Form 1/77**

Patents Act 1977

① Title of invention

1 Please give the title of the invention Method for Dram Sensing Current Control

② Applicant's details

☐ **First or only applicant**

2a If you are applying as a corporate body please give:
Corporate name

Country (and State
of incorporation, if
appropriate)

2b If you are applying as an individual or one of a partnership please give in full:

Surname FOSS
Forenames Richard C

2c **In all cases**, please give the following details:

Address P.O. Box 13285
 Kanata
 Ontario

UK postcode
(if applicable)

Country Canada, K2K 1X4

ADP number
(if known)

~~3183183000~~ AB

3866779001

2d, 2e and 2f: If there are further applicants please provide details on a separate sheet of paper.

For further applicants please see attached sheet.

③ An address for service in the United Kingdom must be supplied

Please mark correct box

3b: If you have appointed an agent, all correspondence concerning your application will be sent to the agent's United Kingdom address.

Second applicant (if any)

2d If you are applying as a corporate body please give:

Corporate name

Country (and State
of incorporation, if
appropriate)

2e If you are applying as an individual or one of a partnership please give in full:

Surname GILLINGHAM

Forenames Peter B.

2f In all cases, please give the following details:

Address 116 Palomino Drive

Kanata

Ontario

UK postcode
(if applicable)

Country Canada K2M 1N4

ADP number
(if known)

~~67443002~~ 5581848002

③ Address for service details

3a Have you appointed an agent to deal with your application?

Yes ☒ No ☐ → go to 3b

↓
please give details below

Agent's name T. Z. GOLD & COMPANY

Agent's address 9 Staple Inn

London

Postcode WC1V 7QH

Agent's ADP
number 760001

3b If you have not appointed an agent please give a name and address in the United Kingdom to which all correspondence will be sent:

Name

Address

Postcode

ADP number
(if known)

Daytime telephone
number (if available)

- ⑦ The answer must be 'No' if:
- any applicant is not an inventor
 - there is an inventor who is not an applicant, **or**
 - any applicant is a corporate body.

⑧ Please supply duplicates of claim(s), abstract, description and drawing(s).

Please mark correct box(es)

- ⑨ You or your appointed agent (see Rule 90 of the Patents Rules 1990) must sign this request.

Please sign here →

A completed fee sheet should preferably accompany the fee.

⑦ Inventorship

7 Are you (the applicant or applicants) the sole inventor or the joint inventor?

Please mark correct box

Yes ☒

No ☐

A Statement of Inventorship on Patents Form 7/77 will need to be filed (see Rule 15).

⑧ Checklist

8a - Please fill in the number of sheets for each of the following types of document contained in this application.

Continuation sheets for this Patents Form 1/77

0

Claim(s)

7

Description

12

Abstract

1

Drawing(s)

1

8b Which of the following documents also accompanies the application?

Priority documents (please state how many)

0

Translation(s) of Priority documents (please state how many)

0

Patents Form 7/77 – Statement of Inventorship and Right to Grant (please state how many)

0

Patents Form 9/77 – Preliminary Examination/Search

1

Patents Form 10/77 – Request for Substantive Examination

0

⑨ Request

I/We request the grant of a patent on the basis of this application.

Signed

[Signature]

Date 5th April, 1991
(day month year)

Please return the completed form, attachments and duplicates where requested, together with the prescribed fee to:

☐ **The Comptroller
The Patent Office
State House
66-71 High Holborn
London
WC1R 4TP**

Please give the date in all number format, for example, 31/05/90 for 31 May 1990.

Name of Third Applicant

ROBERT HARLAND,
P.O. Box 314,
Carp,
ONTARIO,
Canada, KOA 1LO

3024344001

Am 42/22
Ac 3
13/5/91

Name of Fourth Applicant

MASAMI MITSUHASHI,
57-1 Sumiyoshi,
Oizumi Ora,
Gunma,
JAPAN.

5561462001

Name of Fifth Applicant

ATSUSHI WADA,
9-67 Azanashinoki,
Motojuku, Okazaki,
Aichi,
JAPAN.

558197001

METHOD FOR DRAM SENSING CURRENT CONTROL
FIELD OF THE INVENTION;

This invention relates to semiconductor dynamic random access memories (DRAMs) and in particular to apparatus and methods for controlling the sensing of bit lines.

BACKGROUND TO THE INVENTION:

A DRAM is generally formed of an array of bit storage capacitors which are accessed via word lines and bit lines, the word lines being located in rows and the bit lines being located in columns. The capacitors are coupled via access transistors to the bit lines upon being enabled by the word lines; each capacitor is thus associated with the intersection of a bit line and word line.

In high speed DRAMs, the bit lines are usually provided as a folded bit line (pairs of complementary bit lines), with a sense amplifier connected to both bit lines of a folded bit line. During a read operation the charge stored on a capacitor is dumped on one of the lines of the folded bit line, and the sense amplifier senses the resulting differential in potential between the two lines of a folded bit line, applying full logic voltage levels to the bit lines which both restore the charge on the storage capacitors and apply full logic levels to data buses to which the bit lines are coupled.

Bit lines typically have a capacitance of around 0.2 - 0.5 pF. During sensing, current being passed through the sense amplifier to provide full logic voltage levels on the bit lines is consumed in charging the capacitance of the bit lines. The bit line voltage differential must exceed a certain noise margin before the levels on the bit lines can be read to the databuses. Clearly the voltage differential on the lines of the bit lines must be above that certain level, which requires a substantial capacitor

charging time, which in turn results in a slowed sensing interval.

5 A technique for attempting to deal with bit line capacitance is to insert an isolation device to isolate the sense nodes associated with the sense amplifier from the bit lines during the initial sensing period. In other words, a memory capacitor associated with one of the lines of the bit line is enabled to dump its charge on one bit line, following 10 which both bit lines are completely isolated from the sense amplifier. Since the small amount of capacitance associated with the sense node retains some charge differential, subsequent enabling of the sense amplifier causes it to sense this differential, 15 and to apply the full logic level to the sense nodes for application to the databus. Since the sense nodes are now completely isolated from the bit lines, the bit lines need not be charged up by the power supply associated with the sense amplifier, and the 20 time for charging the bit line capacitances thus is substantially eliminated.

However since the capacitance associated with the sense nodes isolated from the bit lines is so small, only a fraction of the total charge 25 differential is available for sensing. This is dangerous, in the sense that the differential can be marginal, and an erroneous bit sensed. In addition, operation of the isolators introduces an additional step in a memory access sequence, sacrificing memory 30 speed.

It has also been found that the conductive tracks which carry the sense amplifier clock signals must supply considerable current in order to provide, for all sense amplifiers on the 35 chip, full logic levels. That current must not only charge the bit lines and sense nodes, but also the databuses. The conductive tracks across the

charge differential between its sense nodes, the sense amplifier applies full logic voltage level to the sense nodes, which is applied to the databuses. However due to the voltage drop across the isolating FET, there is significantly less current consumed in charging the bit line capacitance. As a result the sense nodes reach full logic levels considerably faster than in the prior art.

Some time after sensing is started, the gate source bias of the isolating FET is increased to allow bit lines to be charged to full logic levels (overcoming the threshold voltage drop in the FET). This allows bit line charging current to be distributed over time.

According to an embodiment of the present invention, a dynamic random access memory (DRAM) is comprised of a plurality of bit storage capacitors, a folded bit line for receiving charge stored on one of the capacitors, having bit line capacitance, a sense amplifier having a pair of sense nodes for sensing a voltage differential across the sense nodes, apparatus connected to the bit line and the sense nodes for imperfectly isolating the sense nodes from the bit line whereby current can leak therethrough, apparatus for enabling the sense amplifier and for disabling the isolating apparatus and thereby removing the isolation between the sense amplifier and the bit line, whereby current passing through the sense amplifier to the sense nodes is enabled to charge the bit line capacitance through the isolating apparatus to predetermined logic voltage level.

In accordance with another embodiment of the invention a dynamic random access memory (DRAM) is comprised of a plurality of bit lines and associated sense amplifiers, the bit lines being arrayed across an integrated circuit chip and the sense amplifiers being disposed in a row, a pair of

semiconductor integrated circuit contains resistance, and the heavy clock current passing down the tracks creates a voltage difference. This creates a significant differential in the speed of operation of sense amplifiers close to the sense amplifier clock drivers from those at the far ends of the tracks. Access of data from the memory must be slowed to accommodate the slowest sense amplifier.

SUMMARY OF THE INVENTION:

One embodiment of the present invention uses an isolation device as in the prior art described above, but utilizes an imperfect isolation device which can be enabled over an interval and in addition provide a voltage drop. Preferably the isolation device is a field effect transistor (FET) which has its source drain circuit in series between a sense node and an associated bit line. The gate of each FET is held at a voltage which maintains it imperfectly open, and changes to a level which allows each FET to conduct when the sense amplifier operates (e.g. its gate-source voltage is similar to the logic level supplied by the sense amplifier). The imperfect isolation referred to herein means that the source-drain of the FET is in a high resistance state, but allows some charge leakage through it.

Thus when the memory capacitor dumps its charge on the associated bit line, the charge leaks through the imperfect isolation device to the associated sense node of the sense amplifier. During a first part of the sense cycle the voltage on the gate of each isolating field effect transistor is changed to the logic level which is to be applied to the sense amplifier. Due to the leakage through the imperfect isolating device, charge from the memory capacitor leaks to the sense node.

During a subsequent portion of the sense interval, the sense amplifier is enabled. Due to the

low resistance power supply conductors extending in parallel with the row for carrying logic high level and logic low level voltages, sense amplifier enabling signal conductors extending across the chip accessible to the sense amplifiers, apparatus for coupling sense inputs of the sense amplifiers to the power supply conductors, and apparatus coupling the sense amplifier enabling signal conductors to the apparatus for coupling sense inputs, for enabling passage of current resulting from the logic high level and low level voltages to the sense amplifiers.

In accordance with another embodiment of the present invention a dynamic random access memory (DRAM) is comprised of a plurality of bit storage capacitors, a folded bit line for receiving charge stored on one of the capacitors having bit line capacitance, a sense amplifier having a pair of sense nodes for sensing a voltage differential across the sense nodes, the sense amplifier having respective sense enable and restore enable inputs for providing full high and full low logic levels respectively to the sense nodes, power supply apparatus for providing full high and full low logic level voltages, a pair of field effect transistors, one having its source-drain circuit connected between the restore enable input and the high logic level power supply voltage and the other having its source-drain circuit connected between the sense enable input and the power supply low-logic level power supply voltage, and apparatus for providing restore and sense signals to gates of the one and other field effect transistors respectively, whereby restore and sense current is supplied to the sense amplifier from the power supply apparatus rather than from the apparatus for providing restore and sense signals.

In accordance with a further embodiment of the invention, a method of sensing in a folded bit

line type of dynamic random access memory (DRAM) having a bit storage capacitor for coupling to the bit line and a sensing amplifier having sense nodes, is comprised of the steps of imperfectly isolating the sense nodes of the sensing amplifier from the bit line using an imperfectly isolating apparatus, coupling the capacitor to the bit line thereby dumping its charge thereon, leaking the charge through the imperfect isolating apparatus to one of the sense nodes thereby causing a voltage differential across the sense nodes, sensing the differential by the sense amplifier, and applying full high and low logic levels respectively to the sense nodes, and, inhibiting isolation of the sense nodes from the bit line, whereby full logic levels are applied to the complementary bit lines.

In accordance with another embodiment of the present invention, in order to make substantially more equal the enabling time of the sense amplifiers closest to their clock driver and those farthest away, the enabling inputs to the sense amplifiers are connected through local pull down field effect transistors to local power supply tracks which have little resistance from one end to the other of the integrated circuit memory. The gates of these pull down transistors are connected to the sense amplifier clock conductive tracks since very little current is required by the gates of those transistors, and very little voltage drop thus occurs between the near and far ends of the integrated circuit. Accordingly enabling of the sense amplifiers is substantially speeded at locations remote from the near end sense amplifiers, and there is substantially reduced differential in enabling speed between the near and far end of the sense amplifiers.

In order to reduce the number of transistors required, groups of sense amplifiers may be coupled to the same pull down transistors.

BRIEF INTRODUCTION TO THE DRAWINGS:

5 A better understanding of the invention will be obtained by reference to the detailed description below, in conjunction with the following drawings, in which:

10 Figure 1 is a schematic diagram of a portion of a bit line circuit and sense amplifier in accordance with the prior art,

Figure 2 is a schematic diagram of a portion of a bit line circuit and sense amplifier in accordance with the present invention, and

15 Figure 3 is a waveform diagram used to describe the function of the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS OF THE INVENTION:

20 Turning first to Figure 1, a portion of a prior art bit line and sense amplifier circuit is shown. Bit storage capacitors 1A and 1B are coupled through field effect transistors (FETs) 2A and 2B to complementary bit lines BL and /BL of a folded bit line. The gates of transistors 2A and 2B are
25 connected to word lines WL_n and WL_{n+1} in a well known manner.

A sense amplifier 3 is connected to the bit lines also in a well known manner. The bit lines are coupled to databuses DB and /DB via FETs 4A and
30 4B.

The sense amplifier 3 is formed of a pair of N-channel transistors having their series connected source-drain circuits connected across the bit lines of the folded bit line, their junction
35 being connected to an active low logic level source $/\phi_B$, and a pair of P-channel FETs having their series connected source-drain circuits connected across bit

lines BL and /BL, their junction being connected to an active high level source ϕ_R . The gates of the N and P-channel transistors connected to a first bit line are connected together and to the other bit line, and the gates of the transistors connected to the other transistor are connected together and to the first bit line.

In operation a transistor e.g. 2B is enabled from a word line, and the charge, representing a bit, stored on a capacitor e.g. 1B is dumped to the associated bit line /BL. This creates a voltage differential between bit lines BL and /BL which appears across sense nodes SA and SB. When the logic levels ϕ_S and ϕ_R are applied to the sense amplifier 3, the voltage differential causes the circuit to latch, applying the full logic levels of ϕ_S and ϕ_R to the bit lines. This restores the charge on the capacitor 1B to full logic level. Upon enabling of the transistors 4A and 4B by the signal ϕ_{yi} , the resulting full logic level on the bit lines is applied to the databuses DB and /DB.

Associated with each bit line is an inherent capacitance 5A and 5B, which results from the length and breadth of the bit line track on the semiconductor and the substrate. Those capacitances 5A and 5B must be charged by the current from the power supply supplying the full logic levels ϕ_S and ϕ_R . This takes a considerable period of time and current requirement.

Therefore isolators 6A and 6B have been used to isolate the bit line from the sensing nodes SA and SB associated with the sense amplifier. The isolators are devices which completely isolate the bit lines from the sense nodes.

As noted earlier, while the aforementioned device was successful in isolating the bit lines from the sense nodes, thus eliminating the requirement to

charge the bit line capacitances 5A and 5B during the initial part of the sensing interval, the differential between sense nodes was sometimes uncertain and sometimes small, and was affected by noise, or even being below the noise level.

Accordingly an incorrect bit value could be sensed.

In addition, since the isolator must be turned on and off, additional steps in the memory access sequence must be performed. Further, the isolator must be inhibited in order to restore the logic level to the memory capacitor and indeed, if an incorrect bit were read, the restored bit value would also be incorrect. Clearly both speed and reliability of the memory were sacrificed.

Figure 2 illustrates an embodiment of the present invention. An imperfect isolation device 8A and 8B, driven from a source ϕ_{IN} is connected in series between each bit line and each sense node. In the embodiment shown in Figure 2 the imperfect isolation devices are N-channel enhancement mode FETs 8A and 8B. However alternatively, or in addition, P-channel enhancement mode FETs are connected in series between each bit line and each sense node. The gates of the transistors 9A and 9B are connected together to a logic source ϕ_{IP} .

With reference to Figures 2 and 3, operation of the device is as follows. At the beginning of an active cycle the voltage ϕ_{IN} is brought from a boosted level, e.g. V_{pp} to a lower level that still allows cell charge to flow to the sense amplifier as noted, e.g. V_{dd} . Then, as described earlier, either transistor 2A or 2B is enabled, causing the charge on either bit storage capacitor 1A or 1B to be dumped on an associated bit line. Charge on the bit line leaks through the high resistance source-drain circuit transistor 8A or 8B (assuming transistors 9A and 9B are not present) to

the sense node SA or SB, charging the small capacitance associated therewith.

Subsequently the sense amplifier 3 is enabled by applying high logic level ϕ_s and low logic level ϕ_R , as described earlier. The sense amplifier is caused to apply the full logic levels ϕ_s and ϕ_R to the sense nodes SA and SB, latching due to the differential thereacross. However due to the voltage drop between the sources and drains of transistors 8A and 8B, bit line capacitances 5A and 5B will only be charged up to a reduced voltage less than full logic level applied to the sense nodes. Since capacitances 5A and 5B are charged a reduced amount, the sensing interval is considerably reduced from the prior art; the sensing is faster because the sense node voltage differential develops faster for the same sense current budget. Data can be read out over the data bus by enabling column access transistors 4A and 4B, as soon as a sufficient potential exists across the sense nodes. Hence memory access time is improved by the isolation devices. While the restore charge on capacitors 1A and 1B is less than full logic level, they can be fully restored after column access.

After the peak current has occurred in the first stage of sensing the ϕ_{IN} level is brought back up to the boosted level V_{pp} to allow full restore of the bit lines. This causes a second peak in sensing current. Compared to prior art sensing current peaks are lower and are distributed over time.

It was noted earlier that P-channel transistors 9A and 9B could be used in place of transistors 8A and 8B, or in series therewith as shown in the figure. If P-channel transistors are used, their gates should initially be at a ϕ_{IP} level V_{bb} , and are raised to a level V_{ss} during the initial

part of sensing when a high impedance isolation device is required.

It had been noted earlier that resistive voltage drops in the conductive tracks in the semiconductor memory from the sense amplifier driver circuits to the far end of the array cause quick sensing at the near end of the array (close to the sense amplifier driver circuits) and slow (retarded) sensing at the far end of the array. Thus memory access must be delayed to accommodate the sensing of the slowest column.

According to another embodiment of the invention, rather than driving the logic $/\phi_S$ and ϕ_R input leads of the sense amplifiers directly from the sense amplifier drivers, local pull down FETs or pull up FETs are used. Indeed, these FETs may be shared among several sense amplifiers in adjacent columns.

As shown in Figure 2, rather than the sense amplifier being connected to $/\phi_S$ and ϕ_R logic sources, they are connected through the source-drain circuits of FETs 12A and 12B to voltage sources V_{dd} and ground (V_{SS}) respectively. The gates of transistors 12A and 12B are driven from the $/\phi_R$ and ϕ_S logic sources respectively.

The ground and V_{dd} power tracks on an integrated circuit memory normally are of low resistance. Therefore the provision of those sources to the sense amplifiers is through short and low resistance conductors.

However since the $/\phi_R$ and ϕ_S logic signals driving the gates of transistors 12A and 12B require only a small amount of current, there will be a considerably reduced voltage drop in their conductive tracks from one end of the memory to the other. Thus the difference in operation time of the sense amplifiers between the near and far ends is

considerably reduced, and can be considerably increased in speed over prior art DRAMs.

5 The result of the last-described embodiment is increased reliability, since leaky bit lines which have been deprogrammed will not affect sense line current in other bit lines, if local sense clock drivers are shared only among bit lines with the same redundancy address. No additional power supplies are required other than those normally on the chip.

10 The result of the above embodiments is increase in sensing speed and more uniformity of sensing speed across a large DRAM.

15 It should be noted that either of the embodiments can be used separately or in conjunction. For example, N-channel bit line isolation devices could be used in conjunction with local sensing amplifier enabling pull downs as described, to control peak V_{dd} current and V_{ss} current respectively.

20 A person understanding this invention may now conceive of alternative structures and embodiments or variations of the above. All of those which fall within the scope of the claims appended hereto are considered to be part of the present invention.

25

CLAIMS

1. A dynamic random access memory (DRAM) comprising:

- (a) a plurality of bit storage capacitors,
- (b) a folded bit line comprised of a
5 complementary bit line pair for receiving charge stored on one of said capacitors, having bit line capacitance,
- (c) a sense amplifier having a pair of sense nodes for sensing a voltage differential across said
10 sense nodes,
- (d) means connecting said bit line to said sense nodes for imperfectly isolating said sense nodes from the bit line whereby current can leak therethrough,
- 15 (e) means for enabling said sense amplifier and establishing full predetermined logic levels across said sense nodes,
- (f) means for disabling said isolating means and thereby removing said isolation,
20 whereby current passing through the sense amplifier to said sense nodes is enabled to charge said bit line capacitance through said isolating means to a predetermined logic voltage level.

2. A DRAM as defined in claim 1 in which said isolating means is a pair of N-channel enhancement mode field effect transistors each having a source-drain circuit in series with a bit line of the bit
5 line pair.

3. A DRAM as defined in claim 1 in which said means for disabling is comprised of a voltage source applied to gates of each field effect transistor having an initial voltage level which is higher than
5 said logic voltage level and a following voltage

level which is equal to said logic level, and at a later time a voltage equal to the initial voltage level.

4. A DRAM as defined in claim 1 in which said isolating means is a pair of P-channel enhancement mode field effect transistors each having a source-drain circuit in series with a bit line of the bit line pair.

5. A DRAM as defined in claim 1 in which said means for disabling is comprised of a voltage source applied to gates of each field effect transistor having an initial voltage level which is lower than said logic voltage level and a following voltage level which is equal to said logic level, and at a later time a voltage equal to said initial voltage level.

6. A dynamic random access memory (DRAM) comprising:

- (a) a plurality of bit storage capacitors,
- (b) a folded bit line for receiving charge stored on one of said capacitors having bit line capacitance,
- (c) a sense amplifier having a pair of sense nodes for sensing a voltage differential across said sense nodes, the sense amplifier having respective sense enable and restore enable inputs for providing full high and full low logic levels respectively to said sense nodes,
- (d) power supply means for providing full high and full low logic level voltages,
- (e) a pair of field effect transistors, one P-channel enhancement mode having its source-drain circuit connected between said restore enable input and the high logic level power supply voltage and the

20 other N-channel enhancement mode having its source-
drain circuit connected between the sense enable
input and the low logic level power supply voltage,
and

25 (f) means for providing restore and sense
signals to gates of said one and other field effect
transistors respectively,

whereby restore and sense current is supplied
to said sense amplifier from said power supply means
rather than from said means for providing restore and
sense signals.

30

7. A dynamic random access memory (DRAM)
comprising a plurality of bit lines and associated
sense amplifiers, the bit lines being arrayed across
an integrated circuit chip and the sense amplifiers
5 being disposed in a row, a pair of low-resistance
power supply conductors extending in parallel with
said row for carrying logic high level and logic low
level voltages, sense amplifier enabling signal
conductors extending across said chip accessible to
10 said sense amplifiers, means for coupling sense
inputs of said sense amplifiers to said power supply
conductors, and means coupling said sense amplifier
enabling signal conductors to enabling inputs of said
means for coupling sense inputs, for enabling passage
15 of current resulting from said logic high level and
low level voltages to said sense amplifiers.

8. A DRAM as defined in claim 7 in which said
means for coupling sense inputs of said sense
amplifiers is comprised of field effect transistors
having their gates connected to said sense amplifier
5 enabling signal conductors, said gates forming said
enabling inputs.

9. A DRAM as defined in claim 8 in which the sense inputs of groups of said sense amplifiers are connected together to the same field effect transistor drain terminal.

5

10. A DRAM as defined in claim 1, further comprising:

(a) the sense amplifier having sense enable and restore enable inputs for providing full high and full low logic levels respectively to said sense nodes,

5

(b) power supply means for providing full high and full low logic level voltages,

10

(c) a pair of field effect transistors, one having its source-drain circuit connected between said restore enable input and the high logic level power supply voltage and the other having its source-drain circuit connected between the sense enable input and the low logic level power supply voltage, and

15

(d) means for providing restore and sense signals to gates of said one and other field effect transistors respectively,

20

whereby restore and sense current is supplied to said sense amplifier from said power supply means rather than from said means for providing restore and sense signals.

5

11. A DRAM as defined in claim 1, further comprising a plurality of bit lines and associated sense amplifiers, the bit lines being arrayed across an integrated circuit chip and the sense amplifiers being disposed in a row, a pair of low-resistance power supply conductors extending in parallel with said row for carrying logic high level and logic low level voltages, sense amplifier enabling signal conductors extending across said chip accessible to

10 said sense amplifiers, means for coupling sense
inputs of said sense amplifiers to said power supply
conductors, and means coupling said sense amplifier
enabling signal conductors to enabling inputs of said
means for coupling sense inputs, for enabling passage
15 of current resulting from said logic high level and
low level voltages to said sense amplifiers.

12. A DRAM as defined in claim 3, further
comprising a plurality of bit lines and associated
sense amplifiers, the bit lines being arrayed across
an integrated circuit chip and the sense amplifiers
5 being disposed in a row, a pair of low-resistance
power supply conductors extending in parallel with
said row for carrying logic high level and logic low
level voltages, sense amplifier enabling signal
conductors extending across said chip accessible to
10 said sense amplifiers, means for coupling sense
inputs of said sense amplifiers to said power supply
conductors, and means coupling said sense amplifier
enabling signal conductors to enabling inputs of said
means for coupling sense inputs, for enabling passage
15 of current resulting from said logic high level and
low level voltages to said sense amplifiers.

13. A DRAM as defined in claim 5, further
comprising a plurality of bit lines and associated
sense amplifiers, the bit lines being arrayed across
an integrated circuit chip and the sense amplifiers
5 being disposed in a row, a pair of low-resistance
power supply conductors extending in parallel with
said row for carrying logic high level and logic low
level voltages, sense amplifier enabling signal
conductors extending across said chip accessible to
10 said sense amplifiers, means for coupling sense
inputs of said sense amplifiers to said power supply
conductors, and means coupling said sense amplifier

enabling signal conductors to enabling inputs of said means for coupling sense inputs, for enabling passage
15 of current resulting from said logic high level and low level voltages to said sense amplifiers.

14. A DRAM as defined in claim 11 in which said means for coupling sense inputs of said sense amplifiers is comprised of field effect transistors having their gates connected to said sense amplifier
5 enabling signal conductors, said gates forming said enabling inputs.

15. A DRAM as defined in claim 14 in which the sense inputs of groups of said sense amplifiers are connected together to the same field effect transistor drain terminal.

5

16. A method of sensing in a folded bit line type of dynamic random access memory (DRAM) having a bit storage capacitor for coupling to the bit line and a sensing amplifier having sense nodes,
5 comprising:

(a) imperfectly isolating the sense nodes of the sensing amplifier from the bit line using an imperfect isolating means,

(b) coupling the capacitor to the bit line, thereby dumping its charge thereon,
10

(c) leaking said charge through the imperfect isolating means to one of the sense nodes, thereby causing a voltage differential across said sense nodes,

(d) sensing said differential by said sense amplifier and applying full high and low logic voltage levels respectively to said sense nodes,
15

(e) inhibiting isolation of said sense nodes from said bit line, whereby full logic levels are

20 applied to complementary bit lines of said folded bit line.

5 17. A method as defined in claim 16, in which the isolating means is comprised of the source-drain circuits of a pair of enhancement mode field effect transistors respectively connected between the sense nodes and the complementary bit lines of the folded bit line, and said isolating step is comprised of applying an inhibiting voltage to gates of said field effect transistors, and the inhibiting isolating step is comprised of changing the inhibiting voltage to
10 the same voltage as one of said full logic voltage levels, whereby upon application of said full logic levels to said sense nodes during the sensing step, a field effect transistor having a gate voltage closest to a logic level applied to a sense node to which it
15 is connected is caused to inhibit current flow into the bit line.

18. A DRAM according to claim 1, 6 or 7 substantially as herein described with reference to and as shown in Figs. 2 and 3 of the accompanying drawings.

19. A method according to claim 16, substantially as herein described with reference to and as shown in Figs. 2 and 3 of the accompanying drawings.

METHOD FOR DRAM SENSING CURRENT CONTROL

Apparatus and methods for controlling the sensing of bit lines which facilitates the distribution of bit line charging current to be distributed any time, and facilitates the fast raising of the sense nodes to full logic levels. An embodiment is comprised of a plurality of bit storage capacitors, a folded bit line for receiving charge stored on one of the capacitors, having bit line capacitance, a sense amplifier having a pair of sense nodes for sensing a voltage differential across the sense nodes, apparatus connected to the bit line and the sense nodes for imperfectly isolating the sense nodes from the bit line whereby current can leak therethrough, apparatus for enabling the sense amplifier and for disabling the isolating apparatus and thereby removing the isolation between the sense amplifier and the bit line, whereby current passing through the sense amplifier to the sense nodes is enabled to charge the bit line capacitance through the isolating apparatus to predetermined logic voltage level. Another embodiment is comprised of a plurality of bit lines and associated sense amplifiers, the bit lines being arrayed across an integrated circuit chip and the sense amplifiers being disposed in a row, a pair of low resistance power supply conductors extending in parallel with the row for carrying logic high level and logic low level voltages, sense amplifier enabling signal conductors extending across the chip accessible to the sense amplifiers, apparatus for coupling sense inputs of the sense amplifiers to the power supply conductors, and apparatus coupling the sense amplifier enabling signal conductors to the apparatus for coupling sense inputs, for enabling passage of current resulting from the logic high level and low level voltages to the sense amplifiers.

(Fig. 2)




FIG 1
PRIOR ART




FIG 2




FIG 3